



BS Series Battery Separators

FEATURES

- Microprocessor controlled
- Provides priority for charging only the starter battery first
- Prevents excessive discharging of the starter battery
- Automatic detection for 12 or 24 Vdc system
- Easy to install - does not require changing of the existing circuit of the alternator
- Bidirectional
- No voltage drop
- 2 years warranty

APPLICATIONS

- Battery Separators are designed for use with 2 sets of batteries.
- It is recommended that these products be used with inverters
- When an auxillary battery is in use
- Ideal for:
- RV / Automotive



100 AMPS

TECHNICAL SPECIFICATIONS

Model	BS 100 Dual
Continuous current	100 A
Peak current	300 A (250msec)
Connect voltage	13.2 or 26.4 VDC
Disconnect voltage	12.8 or 25.6 VDC
Standby current	<5mA (12V) <5mA (24V)
Start contact	Yes
Micro switch for remote status indication	No
Voltage stability	±2%
Weight	0,11 Kgs
Dimensions (HXWXD)mm	46X46X80

Technical Specifications subject to change without notification